



## LANDSCAPE LIGHT INSTALLATION INSTRUCTIONS

Installation is to be by a qualified electrician in accordance with all applicable electric codes.

1. Landscape light fixture by TWO HILLS STUDIO. Actual shape may vary.
2. Inner metal pan (Also acts as j-box). Attach to concrete footing by others with appropriate fasteners.
3. Electrical conduit(s) by others. Turn off electricity to electrical conduit before installing the fixture  
Extend the conduit containing supply wires to 1/2" above the top of the finished concrete footing.
4. Connect ground wire from conduit to ground wire from the inner metal pan cap. Connect black & white wires from the inner metal pan cap to corresponding black & white wires from conduit using appropriate wire nuts.
5. Inner metal pan cap. Fasten metal cap to inner metal pan with screws provided.
6. Fasten the fixture to the inner metal pan with the set screws on all sides. Adjust the fixture to be plumb and level by shimming the inner metal pan.
7. In most models the roof is removable for relamping by removing set screws indicated on the fixture. Use only the lamps (bulbs) indicated on the fixture.
8. Fixtures are for 120 volt power supply unless labeled otherwise. Connect only to a power supply of the proper voltage.